



Remote control settings presence det.

EE807

Architecture

Number of keys	18
----------------	----

Configuration

Module	télécommande
--------	--------------

Compatibility

Sensors associated	EE81x, TCC52x
--------------------	---------------

Controls and indicators

- 3 configuration ranges for control, switch-off delay, brightness threshold
- 15 push-buttons with integrated status-LED

Reach distance

Max. transmission range	3m
-------------------------	----

Battery

Battery service life [years]	~ 2,5
Number and type of replacement batteries	1x 3V CR2032

Detection

- RC6 code

Dimensions

Dimensions (LLxwwxhh)	70x10x120
-----------------------	-----------

LED control

- additional acknowledgement LED for displaying the IR transmission

Settings

- setting of the brightness threshold manually, by default values or teach-in mode
 - default settings can be selected for the brightness threshold daylight, office, corridor
-

Accessories included

Accessory type	Manual transmitter for movement sensor
----------------	--

Equipment

- 2 configuration memories for identical configuration of several presence detectors
-

Instructions

- also for KNX applications - KNX IR presence detector
-